

# G900

Tecnologia: 2G

## Servidores

 SP: 49.12.92.6 - dns.mine.nu | Porta = 6013

 AL: 168.119.25.88 - ese.mine.nu | Porta = 6013

 SC: 167.235.35.219 - sc.mine.nu | Porta = 6013

 PI: 167.235.34.85 - dns.alfarastreamento.com | Porta = 6013

 SP Sorocaba: 65.21.232.27 - sastracker.mine.nu | Porta = 6013

 MA: 65.21.249.189 - telensat.mine.nu | Porta = 6013

# Comandos

Porta(s): 6013

## Configuração Inicial

**Comando 1:** APN123456 jw.claro.com.br claro claro (**Comando de APN - Exemplo de APN da Claro**)

**Necessário alterar o comando de acordo com a APN utilizada**

**Comando 2:** ADMINIP123456 dns.mine.nu 6013 (**Comando para conexão do rastreador na plataforma**)

**O IP/DNS devem ser substituídos de acordo com o servidor**

**Comando 3:** TIMEZONE123456 (**Configuração do fuso horário**)

**Comando 4:** ITV123456 60 500 (**Tempo de transmissão**)

---

## Demais comandos

**Comando:** setimei123456 355126070674548 (**Alterar número de IMEI de equipamento**)

**Comando:** begin123456 (**Reiniciar o equipamento com as configurações iniciais**)